

CAR RADIO MADRID 200 BT



Subject to availability and technical modification.



Shortened installation depth



RDS Tuner



Bluetooth



USB



USB



4x40W



Sound Presets



X-BASS



Permanent memory



Ignition logic

Sales Start
AUTUMN 2020

Order Number
2 001 020 000 001

EAN-Code
4 260 499 852 320

Highlights

- RDS Tuner
- FM (RDS), AM
- Playback formats: MP3, WMA
- Fast playback from USB
- Selectable display modes (file, folder, title, artist, album & playtime)
- Data carrier: USB
- 9-digit display
- Built-in Bluetooth (HFP, A2DP)
- Built-in microphone
- Front USB
- Front-Aux-in
- 4x40 Watt Max.
- 2-channel Preamp-out
- Sound presets (Flat, Rock, Pop, Classic)
- X-Bass
- Red key illumination

CAR RADIO

MADRID 200 BT

2/3

ANALOG RADIO

| | |
|-------------------------------|--|
| Type of tuner | RDS Tuner |
| Wave bands | 3x FM / 2x AM |
| Radio Data System (RDS) | Alternative Frequency (AF) Clock Time (CT) Programme Service Name (PS) Regional Programme (REG) Traffic Announcement (TA) Traffic Program (TP) yes (FMT) |
| Travelstore | yes / no |
| Band Scan / Preset Scan | 15 FM / 15 AM |
| Station memory | lo / dx |
| Sensitivity | yes |
| Interference suppression | yes |
| Frequency response (Hz) -3 dB | 20 – 18.000 |

**BLUETOOTH**

| | |
|-----------------------------|---|
| Supported profiles | HFP,A2DP |
| Audio streaming | yes |
| Pairing (number of devices) | 1 |
| Hands-free calling | yes |
| Microphone | built-in |
| Key functions | accept / hang-up / reject call / redial |
| Phone book access | yes (up to 100 entries by phone) |

**MEDIA-PLAYER**

| | |
|-----------------------------------|--|
| Playback format | MP3, WMA |
| Title display | ID tag, file folder |
| Folder- & file browsing | no |
| Display modes | yes (file, folder, title, artist, album, playtime) |
| Mix (random play) / Repeat / Scan | yes / yes / yes |
| Bitrate (kBit/s) | 32 -320 |

CAR RADIO

MADRID 200 BT

3/3

AUDIO / EQUALIZER

| | |
|-----------------|--------------------------|
| Bass / treble | yes / yes (+/- 7 steps) |
| Balance / fader | yes / yes (+/- 9 steps) |
| X-Bass | yes |
| Sound presets | Flat, Rock, Pop, Classic |

AMPLIFIER

| | |
|-----------------------|-------------|
| Number of channels | 4 |
| Max. power | 4 x 40 Watt |
| Sinus power at 14.4 V | 4 x 20 Watt |

DISPLAY

| | |
|---------------|---------------------------|
| Type / Digits | 1-line / 9 |
| Colour | negative, black and white |
| Clock display | 24 / 12 hrs |

INPUTS

| | |
|--------------------------|-----------------------|
| Antenna (number of) | 1 (FM ISO) |
| USB (number of / type) | 1 (front) |
| Aux-In (number of, type) | 1 front (3,5 mm jack) |

OUTPUTS

| | |
|-------------------------|------------------|
| Loudspeaker (number of) | 4 |
| Pre-amplifier channel | 2-channels (RCA) |
| Pre-amplifier voltage | 1.5 V (rms) |

GENERAL

| | |
|-------------------------------------|-----------------------|
| Software update | via USB |
| Confirmation beep | yes |
| Menu language | English |
| Front panel | Fix panel |
| Panel illumination | Red |
| Permanent preset /& setting storage | yes |
| Ignition logic | yes |
| Weight (kg) | ca. 0,7 |
| Dimensions (mm) | 188 x 58 x 110 |
| ISO connector cable set | yes, 16 pin connector |
| User manual | yes |
| 4-color gift box | yes |

